

D2K – Trail/PEST CAM LIVE 4G

Wildlife – Security – Time-lapse – Pest Control



Key Features



Stronger Reception and Sensor Mode

Dual aerials and access to 2G, 3G and 4G networks



Time Lapse and Sensor Mode

Choose either mode or use both at the same time



Solar Panel or Ultra-Long Battery Life

Easy setup and Plug & Play



Built to Last

A tough, weatherproof clamshell case



All Sim Cards Applicable

Vodafone, Spark or 2Degees functional

Receive photo and video to your mobile phone, email or website, anywhere in the world.

Works on both movement and time lapse setting.



Technical Specifications:

	Simple Set for Pest Control.
	GSM 4G Modem, SIM card Auto-Match.
	Built-in 2.0 TFT colour screen
Trigger Speed:	0.4 second
Lens Model:	100° lens
Photos Resolution:	4032x3024/3264x2448/2560x1920 Mega Pixels 5 Mega Pixels Colour CMOS sensor.
Photo Transmission:	in 5M/8M/12MP original size, 1920x1440(around 350kb) or smaller, with GPS info, date, time, temperature, moon phase and battery shown on the photos. * Multi-shot up to 5 photos, 3 photos burst within 1 second. Black light LED - 57 invisible IR LEDs in total, about 20M/65FT real night vision.
Multi Functions:	Programmable PIR Sensitivity, Dual Timer, Daily Report, App Remote Control, Hybrid Activated (Time Lapse+ Motion Detection), day and night-time operation, TV out, Audio Recording, etc.
Videos:	HD-1080P, recording video up to 10 seconds.
Video Transmission:	up to 10 seconds video transmission; Operation Temperature: -25°C to 60°C; * Weight: around 367g (without batteries)
Estimated Dimensions:	150x120x80mm Waterproof: IP66 SD Card: up to 32GB (not included)
Battery:	12AA (not included)
Included Accessories:	Antenna, strap, USB cable, English Manual
Warranty:	1 Year

Lens Options

Narrow Lens



Wide Lens



Night Vision



Security Case Optional



Security Boxes

Custom fit Security enclosure will help protect your outdoor camera from theft or intentional damage. Weather resistant and easy bolt mounting heavy duty case.

Solar Panel & Holder Optional



Solar Panel Specification :

Model	Parameters
Built-in Li-ion battery	1500mAh/7.4V
Solar panel max output power	2W
Output Voltage	12V
Water proof	IP54
Operation temperature	-22-+158F, -30-+70C
Operation humidity	5%-95%



Solar Panel

Extend your camera's battery life with a lightweight, weatherproof, Swift Solar Panel. Generating enough power for up to 1000 images per day in full sun. Ideal for cameras in remote locations or operating over extended timeframes. Suitable for Swift Cameras only.

Product Prices are all stated exclusive GST

Pest/Trail Cam 4.0CG(NZ)		EX-work Price NZ\$/pc		Packing N.W.: 0.392kg	
1-99pcs	100-299pcs	300-499pcs	500pcs +	Lens	Unit Box
NZ\$795.00	NZ\$695.00	NZ\$625.00	Tbc	Wide	1pcs
1-99pcs	100-299pcs	300-499pcs	Tbc	Lens	Unit Box
NZ\$795.00	NZ\$695.00	NZ\$625.00	Tbc	Narrow	1pcs

Solar Panel		EX-work Price NZ\$/pc		Packing	
1-99pcs	100-299pcs	300-499pcs	500pcs +	Solar Panel	Unit Box
NZ\$89.00	NZ\$84.00	NZ\$79.00	Tbc		1pcs

3000mAH built in Li-ion battery

Solar panel max output power: 2W

Output voltage: 12V, Max output

Current: 1600mA

Security Case		EX-work Price NZ\$/pc		Packing	
1-99pcs	100-299pcs	300-499pcs	500pcs +	Security Case	Unit Box
NZ\$79.00	NZ\$74.00	NZ\$67.00	Tbc	Black	1pcs

New security box for all D2K Pest/Trail Cams cameras Metal, black

Holder		EX-work Price NZ\$/pc		Packing	
1-99pcs	100-299pcs	300-499pcs	500pcs +	Holder	Unit Box
NZ\$15.00	NZ\$12.00	NZ\$11.00	TBC	Black	1pcs

- Micro SD Card, batteries and Sim Card are not included, but optional
- Pre Pay or Data Plan optional with 2Degrees, Vodafone or Spark
- Works on 2G, 3G and 4G networks
- App access optional and included
- Manual on request

Trail Camera Settings

Vodafone Sim - 4G Sim card only

Cam ID: ON
Manual setup for MMS:
MMSC: <http://pvt.vodafone.net.nz/pxtsend>
APN: live.vodafone.com
Proxy: 172.30.38.3
Port: 8080

Manual setup for 4G:

APN: vodafone
SMTP: Default
FTP: Off

2Degrees Sim - 4G Sim card only

Cam ID: ON
Manual setup for MMS:
MMSC: <http://mms.2degreesmobile.net.nz:48090>
APN: mms
Proxy: 118.148.1.118
Port: 8080

Manual setup for 4G:

APN: internet
SMTP: Default
FTP: Off

Spark Sim - Spark 4G Sim card only

Cam ID: ON
Manual setup for mms.
MMSC: <http://smmsc.xtra.co.nz>
APN: internet
Proxy: 210.55.11.73
Port: 80

Manual setup for 4G:

APN: internet
SMTP: Default
FTP: Off

****Make sure to enter in your email and phone number in the "send to" tab****

****Make sure to download the app to be able to control your camera from anywhere! App is called: "TrailCamera"****